

500m2 wall-mounting PDA/S hearing loop amplifier, 7.5A

Part No. PDA7/SW



Overview

A new wall-mounting 7.5A hearing loopamplifier ideal for usein areas up to 500m2.

Intuitive LED interface allows simple set-up of input levels, output current, phantom power &metal compensation

2 x XLR mic/line inputs (selectable) &1 outreach connector.

Class D output stage for maximum efficiency.

Superior audio processing and powerful CPU provide life-likespeech and first class music reproduction.

Fault relay & LEDindicatorsprovide clear indication of operation and fault status.

Industry leading dual action automatic gain control compensates for poor microphone technique.

Line level output for recording or daisy-chaining multiple units to cover larger areas.

Complies with EN62368-1 (Safety requirements for audio/video, information and communication technology equipment).

Technical Specifications

Туре Wall-mounting (requires a permanent 5A fused spur connection to Mains).

Coverage 500m2 approx. 230V 50Hz Mains supply

Output 7.5A loop drive current @ 1 Ohm; Loop output volage 14V.

Max battery size and type

Auxiliary inputs 2 x XLR mic/line inputs with switchable 12V phantom power (on or off) & Outreach.

LED display with level, peak and limit indicators, Mic, 12V, Line, Metal, Outreach, Lock, Loop, Fault, Indicators

Hot and Power Indicators.

Line Input, Microphone, 12V Phantom, Outreach, Metal Comp, Loop Drive. Controls

Connections Mic (3-way pluggable); Line In (3-way connectors); Loop (4 way connector); Outreach (4-way

pluggable connector); Line Out (3-way pluggable connector); Fault Relay (3-way pluggable

connector); 230Va.c. fixed Mains connector.



T 01942 322744

E sales@c-tec.co.uk



















298 (H) x 308 (W) x 74 (D) mm. Product dimensions (mm)

Construction & finish Mild steel zintec, 1mm thick, black powder coated.

IP Rating IP40. 3.35kg Weight

-5°C to +40°C. Max relative humidity: 95%. Operating conditions/temperature

















