

Portable hearing loop kit c/w amplifier, plugtop charger & wall mount shelf

Part No. PL1/K1



Overview

New for 2017 - the PL1/K1 is now supplied with a robust wall-mounting storage shelf.

Ideal for restricted person to person contact in areas such as banks, post offices, small meeting rooms, reception desks, open plan offices and ticket booths.

 $Portable, lightweight design \, means \, the \, system \, can \, be \, moved \, easily \, from \, location \, to \, location.$

Simple one button operation.

Integral high performance microphone.

Excellent sound quality

Five years' expected battery life under normal operating/charging conditions.

Auto shut-off facility (user selectable for 10, 30 or 60 minutes) helps preserve battery life.

Connection of the plug-top charger overrides the timer function to ensure the unit remains operational at all times.

Unit can be used as normal whilst charging.

Technical Specifications

Coverage 1.2m2 approx.

Application/operation Portable.

Mains supply

Kit includes a 230V a.c. plugtop charger.

Max battery size and type Amplifier includes an Integral 12V Valve Regulated Sealed Lead Acid battery.

Auxiliary inputs 2 x Mic (one built-in mic and one 3.5mm remote mic socket for AMT or AMD microphones).

Indicators Power on; input level; charging required; charging in progress; audio-warning of imminent shutdown.

Controls On/off button; adjust auto-shut off timer (note: the auto-shut-off function only applies when the

plugtop charger is not connected to preserve battery life).

Product dimensions (mm) W 271 x H 200 x D 77mm (amplifier). Shelf measures W 260 x H 263 x D 140mm.

Construction & finish Black plastic amplifier with blue 'AFILS' available label; black high impact polystyrene shelf.



T 01942 322744

E sales@c-tec.co.uk

F 01942 829867 **W** www.c-tec.com















C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom



IP Rating IP20.

2.82kg (amplifier); 360g (shelf). Weight

Kit contents $PL1 \ amplifier; \ plug-top \ charger; \ wall \ mounting \ storage \ shelf.$















